

(ري بـمأ تلوف وليك) عـق اـطـلـا

3 روطلا 50 Hz, PF 0.8

ي ئاب رەڭدا دەجىلا	(ESP) ياب دىناتىس قىيا		(PRP) ميارب قىيا		Standby Amper
	kW	kVA	kW	kVA	
400/231	26,40	33,00	24,00	30,00	47,63

محمدي مل. ISO8528 عم قفاوتم ،ESP. نملأ قلعبشلا ردصم عاطقنا لاح يف ؤلومحلل قق اطلا ريغوت يفريغتملا ءابرلكلا لمعتسي (ESP) ياب دئانتس قق اط
طر فملا ليمحتلل

للمعكس هـ تي. ISO8528 مع قفاوتم، PRP. عاطقنا نود فيونسلا لم عمل شاع اس لجأ ن م قلوب محلل قاطلا ريفوت يف ري عتلمأ، ابرطفا لم عتسي (PRP) مارب قفاط
ISO3046 بمسح عاس 12 لم عملأ قرتف يف 10% دئازلا لم عتلمأ لجأ ن م قذحوا عاس

قماع تافصاوم

چڙومڻ لاءِ مڇرو مڻ	AP 33
(زيترو) ددرت لاءِ	50
دوقول عوڻ	Diesel
ٻيڙاڇاڻ لاءِ مٿس استعمال ڪندڙ دنگل لاءِ چڙومڻ	PERKINS 1103A-33G
ٻيڙاڇاڻ لاءِ مٿس استعمال ڪندڙ بوانٽل لاءِ دنگل لاءِ چڙومڻ	ECP 28-VL/4 C
مڻ ڇاڻ لاءِ ٻيڙاڇاڻ لاءِ چڙومڻ	DSE 6120
ڦرڻ لاءِ	AK 21

كـرحملا تافصاوم

كتر حمل	PERKINS
كتر حمل جزومن	1103A-33G
(L) تان او طس آل ددع	3 cylinders - in line
فئو جئتا	105
ئم دئصلا	127
قن او طس آل م ج ح	3.3
ء او ملا طففش	Naturally Aspirated
طغئضلا لدعم	19.25:1
ء عرسل (d/dk)	1500
(رئتا) (رئفلا ءال ماش) ئئزلا ء عس	8.3
(ءئل ام جال) ناصح / ئ عاس طاوول ئك ءئطائئ حال ءقا طلا	31/41,55
(ءئل ام جال) ناصح / ئ عاس طاوول ئك ءئسئئزلا ءقا طلا	28.2/37,80
كتر حمل ءلئك ئئخسئ ءزء ج ددع	1
(طاو) كتر حمل ءلئك ئئخسئ ءزء ج ءقا ط	500
دوقولا عون	Diesel
نقءال مائظو عون	Direct
دوقولا ءخضم عون	Delphi Rotary Type
مكحئتا مائظن	Mechanic
(رمئسم رائئ ئلوف) لئغشئلل ئئابرهلكلا دهئلا	12 Vdc
(ءعاسلا/ءئمكلا) ءعسل او ءئراطبلا	1x55
(رئبم) بوانئمل نئشلا رائئ	65

ق.قبسمل رابخالا نود نم روصول او تار اوسس كئال او تادعمل او ناولال او عي نفل تا فصول او مل او تال يدومل اى ف ل يدعتل ا ق ح لى ع جت نمل ا ظف ا ح ي



دي ربتل ققيرط

Water Cooled

(رتل) (روتيدارلا عم / طقف لجرم) دي ربتل لئاس عس

/10.2

ءاولا رتلف

Dry Type

(عاس/رتل) لمح 100% دن ع دوقولا كلال متسا

7.1

(عاس/رتل) لمح 75% دن ع دوقولا كلال متسا

5.4

(عاس/رتل) لمح 50% دن ع دوقولا كلال متسا

3.9

بوانتمل رايتمل دلوم تافصاوم

Manufacturer

Mecc Alte

ةيراجتمل متمالعو بوانتمل رايتمل دلوم جنوم

ECP 28-VL/4 C

(زتره) ددرتمل

50

(ريبم تلوف وليك) ققاطلا

30

(V) يئابرهمكلا دهجلا

400

روطلا

3

يكي تادموتوالا دهجلا مظنم

DSR

دهجلا مظنم

(+/-)1%

لزعلماظن

H

ةيامحل فنص

IP23

ققاطلا لماع

0.8

(غك) يللكلا دلوملا نزو

141.8

دي ربتل ءاوه

6.6

(مم) حوتفملا عونلا وذي ئابرهمكلا دلوملا تاسايق

لوطلا

1691

ضررعل

970

عافتريال

1221

DRY WEIGHT (kg.)

665

نازخ عس

80

(مم) يئابرهمكلا دلوملا قرج تاسايق

لوطلا

2102

ضررعل

1026

عافتريال

1290

DRY WEIGHT (kg.)

880

نازخ عس

80

ةمدقملا

Sound-attenuated and Weather-protective Enclosures Sound-attenuated and weather protective enclosures for generating sets from Aksa, meet event the sound requirements and provide optimum protection from inclement weather and development by our specialist acoustic engineers. Our modular designed sound insulated canopies provide ease of access for servicing and general maintenance and interchangeable components permitting on-site repair. Enclosures are designed to optimize genset cooling performance, providing you with confidence that genset ratings and ambient capability.

مكحتلا ةحول

قبسمل رابخالا نود نم روصلاو تاراويسكالاو تادعمل او ناولال او ةينفلا تافصاوملاو تاليدوملا يف ليدعتلا قح ىل ع جتنملا ظفاحي.



مكحيتلا قدحو

DSE

مكحيتلا قدحو و ذ ج ذومن

DSE 6120

لاصتالا ذفانم

CANBUS

##CONTROL PANEL IMAGE##

##CONTROL PANEL TABLE##

قز هجال

- DSE, model 6120 Auto Mains Failure control module.
- Battery charger input 198-264 volt, output 27,6 V 5 A (24 V) or 13,8 Volt 5A (12V)
- Emergency stop push button and fuses for control circuits.

CONSTRUCTION and FINISH

-Components installed in sheet steel enclosure. Phosphate chemical, pre-coating of steel provides corrosion resistant surface. Polyester composite powder topcoat forms high gloss and extremely durable finish. Lockable and hinged panel door provides easy access to components.

بي كرتلا

Control panel is mounted on baseframe with steel stand. Located at the right side of the generator set (When you look at the Gen.Set. from Alternator)

مكحيتلا قدحو تادلوملا

The DSE 6120 module has been designed to monitor generator frequency, volt, current, engine oil pressure, coolant temperature running hours and battery volts.

Module monitors the mains supply and switch over to the generator when the mains power fails.

The DSE6120 also indicates operational status and fault conditions, Automatically shutting down the Gen. Set and giving true first up fault condition of Gen. Set failure. The LCD display indicates the fault.

قيراي عم تافصاوم

- Microprocessor controlled.
- LCD display makes information easy to read.
- Automatically transfers between mains (utility) and generator power.
- Manual programming on front panel.
- User-friendly set-up and button layout.
- Remote start.
- Event logging (50) showing date and time.
- Controls: Stop/Reset, Manual, Auto, Test, Start, buttons. An additional push button next to the LCD display is used to scroll through the modules' metering displays.

ساي قلا تارشوم

ENGINE

- Engine speed.
- Oil pressure.
- Coolant temperature.
- Run time.
- Battery volts.
- Configurable timing.

GENERATOR

- Voltage (L-L, L-N).

قابسمل رابخالا نود نم روصلاو تاروايسسكال او تادعمل او ناولال او قينفلا تافصاوملاو تاليدوملا يف ليدعتلا قح و ل ع جتنملا ظفاحي



-Current (L1-L2-L3).

-Frequency.

-Gen. Set ready.

-Gen. Set enabled.

MAINS

-Mains ready.

-Mains enabled.

WARNING

-Charge failure.

-Battery Low/High voltage.

-Fail to stop.

-Low /High generator voltage.

-Under /Over generator frequency.

-Over /Under speed.

-Low oil pressure.

-High coolant temperature.

SHUT DOWNS

-Fail to start.

-Emergency stop.

-Low oil pressure.

-High coolant temperature.

-Over /Under speed.

-Under/over generator frequency.

-Under/over generator voltage.

-Oil pressure sensor open.

-Coolant temperature sensor open.

ELECTRICAL TRIP

-Generator over current.

تارايخ

-Flexible sensor can be controlled with temperature, pressure, percentage (warning/shutdown/electrical trip)

-Local setting parameters and monitoring from PC to control module with USB connection (max 6 mt).

ريياعمل

-Electrical Safety / EMC compatibility

-BS EN 60950 Electrical business equipment.

-BS EN 61000-6-2 EMC immunity standard.

-BS EN 61000-6-4 EMC emission standard

(نحاشل) يكي تاتسالا ةيراطبل موقم

- Battery charger is manufactured with switching-mode and SMD technology and it has high efficiency.

قېسمل رابخال نود نم روصلالو تاراو سسكالو تادعملالو ناولالو ةينفل تافصاوملالتاليدوملالتاليدعتلا قح لىع جتنمل ظفاحي



- Battery charger models' output V-I characteristic is very close to square and output is 5 amper, 13,8 V for 12 volt and 27,6 V for 24 V . Input 198 - 264 volt AC.
- The charger is fitted with a protection diode across the output.
- Connect charge fail relay coil between positive output and CF output.
- They are equipped with RFI filter to reduce electrical noise radiated from the device.
- Galvanically isolated input and output typically 4kV for high reliability.

ياري عم تافصاوم

- Water cooled, Diesel engine
- Radiator with mechanical fan
- Protective grille for rotating and hot parts
- Electric starter and charge alternator
- Starting battery (with lead acid) including rack and cables
- Engine coolant heater
- Base frame design incorporates an integral fuel tank and anti-vibration isolators
- Flexible fuel connection hoses
- Single bearing, class H alternator
- Industrial exhaust silencer and steel bellows supplied separately(for open sets)
- Static battery charger
- Manual for application and installation

ياري تخا تالال

ENGINE

- Fuel-Water Separator Filter
- Low water level alarm
- Oil heater

ALTERNATOR

- Anti-Condensation Heater
- Over sized alternator
- Main line circuit breaker

CONTROL SYSTEM

- Remote annunciator panel
- Remote relay output
- Alarm output relays
- Remote communication with modem
- Earth fault, single set
- Charge Ammeter

TRANSFER SWITCH

- Three or four pole contactor
- Three or four pole motor operated circuit breaker

OTHER ACCESSORIES

قېسملار رابخا نود نم روصال و تار اوسسكال و تادعمل و ناولال او ٲينفل تافصاومل و تاليدومل ٲل ليدعتل قح و لى جتنمل ظفاحي

**Main Fuel Tank**

Automatic or manual fuel filling system

Manual oil drain pump

Residential silencer

Enclosure: weater protective or sound attenuated

Duct adapter (on radiator)

Inlet and outlet motorised louvers

Inlet and outlet acoustic baffles

Trailer

Tool kit for maintenance

Supplied with oil and coolant - 30 °C

Battery isolating switch

تاداهشل

- TS ISO 8528

- TS ISO 9001-2008

- CE

- SZUTEST

- 2000/14/EC